iSMA-B-AAC20



Advanced Application Controller

| MODEL | DESCRIPTION |
|--------------------|---|
| iSMA-B-AAC20 | Advanced Application Controller |
| iSMA-B-AAC20-D | AdvancedApplicationControllerwith DALI protocol |
| iSMA-B-AAC20-M | AdvancedApplicationControllerwith M-Bus protocol |
| iSMA-B-AAC20-LCD | AdvancedApplicationControllerwith LCD display |
| iSMA-B-AAC20-LCD-D | AdvancedApplicationControllerwith LCD display and DALI protocol |
| iSMA-B-AAC20-LCD-M | AdvancedApplicationControllerwith LCDdisplay andM-Busprotocol |



APPLICATION AND USE

The iSMA-B-AAC20 is an advanced control device to building automation and HVAC systems. Using SVM (Sedona Virtual Machine) allows the user to quickly and easily program in real time. Large number of inputs and outputs allows to integrate with other devices and sensors (AAC20 provides 8 UI, 4 DI, 4/6 AO and 4 DO). Legible, fully programmable LCD can be used as simple interface to local operation of system. Built-in RS485 can be used to expand number of I/O by connecting MINI or MIX series I/O modules using Modbus ASCII/RTU. In addition, to increase the versatility of the controller, it supports many open communications protocols: BACnet, Modbus, SOX, DALI, MBus, 1-Wire or oBIX.

The AAC20 is mounted in a housing adapted for DIN rail mounting or directly on a panel. Separate, easy to remove connectors allow quick wiring without removing the entire module.

FEATURES

- Sedona Framework 1.2 support
- Real Time Clock (RTC)
- 2 Fast Ethernet with built-in switch
- RS485 port (Modbus or BACnet)
- Built-in LCD display(option)
- $\bullet \qquad {\sf MicroSD card slot to loghistorical data} and a larms$
- Fast processor with ARM dual core 204MHz

- Built-in Modbusgateway TCP/IP to RS485
- DALI interface: built-inpowersupply (option)
- M-Bus interface: up to 20 devices (option)
- 1-Wire interface
- iSMATool-freeofchargeprogrammingsoft
- Configuration via web
- Built-in visualization web server

TECHNICAL CHARACTERISTICS

| | DESCRIPTION | AAC20 |
|------------------|------------------|---|
| Power supply | Voltage | 24 V AC/DC ± 20% |
| Universal inputs | Number of inputs | 8 |
| | Voltage input | Voltage measurement: 0-10 V DC Input impedance: 100 kΩ Measurement accuracy: ±0.1% Measurement resolution: 3 mV at 12-bit and 1 mV at 16-bit |
| | Current input | Current measurement: 0-20 mA Required external resistor: 200 Ω Measurement accuracy:±1.1% Measurement resolution: 15 μA at 12-bit and 5 μA at 16-bit |
| | Digital input | Output current ~1 mA |

The performances stated in this sheet can be modified without any prior notice.






| | DESCRIPTION | AAC20 |
|--------------------|----------------------------------|---|
| Universal inputs | Resistance input | $\label{eq:measurement} Measurement of resistance: 0-1000 k\Omega $$ Measurement resolution for 20 k\Omega load: 20\Omega at 12-bit and 1\Omega at 16-bit $$ Measurement resolution for PT1000 and NI1000: 0.1\Omega at 16-bit $$ Resistance measurement method: voltage divider$ |
| | Temperature input | Measurement with RTDS (Real Time Digital Simulator) attached Accuracy: ±0.1°C The PT1000 and NI1000 sensors use 16-bit resolution |
| | Measurement resolution | 12-bit (default), 16-bit |
| | Processing time | 10 ms/channel at 12-bit 140 ms/channel at 16-bit |
| | Number of inputs | 4 |
| Digital inputs | Туре | Dry contact or fast pulse counter |
| | Maximum input frequency | 100 Hz saved in EEPROM memory |
| | Number of outputs | 6 |
| | Voltage range | 0-10 V DC |
| Analog outputs | Maximum load current | 20 mA (AO6 up to 5 mA) |
| | Resolution | 12-bit |
| | Accuracy | ±0.5% |
| | Number of outputs | 4 |
| Digital outputs | Resistive load (AC1) | 3 A at 230 V AC or 3 A at 30 V DC |
| | Inductive load (AC3) | 75 VA at 230 V AC or 30 W at 30 V DC |
| | RS485 Interface | Up to 128 devices |
| | RS485 Interrace | Half-duplex |
| COM1 | Communication protocol | Modbus RTU/ASCII (client) |
| | Port | R/12 |
| | Baud rate | 4800-115200 |
| | Power supply for external device | 30 V DC |
| | RS485 Interface | Up to 128 devices |
| | | Half-duplex |
| COM2 | Communication protocol | Modbus RTU/ASCII (client/server) BACnet MS/TP (client/server) |
| | Port | Screw connector |
| | Baud rate | 4800-115200 |
| ETH1 - | Ethernet interface | 2 ports, switch mode |
| | Baud rate | 10/100 Mb/s |
| USB1 | USB 2.0 | USB type A |
| Ingress protection | IP rating | IP 40 for indoor installation |
| Temperature | Storage | -40°C to +85°C (-40°F to +185°F) |
| remperature | Operating | -10°C to +50°C (14°F to 122°F) |
| Humidity | Relative | 5 to 95% RH (without condensation) |
| Screw connectors | Туре | Removable screw terminals |
| | Maximum cable size | 2.5 mm2 (1812 AWG) |
| Housing _ | Material | Self-extinguishing plastic (PC/ABS) |
| | Mounting | DIN (DIN EN 50022 norm) |
| Dimensions | Width | 110 mm/4.33 in |
| | Length | 106 mm/4.17 in |
| | Height | 62 mm/2.44 in |







Power Supply





Communication



Universal Inputs









Digital Inputs

Analog Outputs



Digital Outputs




BUILT-IN VISUALIZATION WEB SERVER


The visualization web server allows for displaying the parameters and statuses, setting time schedules, and controlling the unit. Visualization can be fully customized to fit the user needs. The web server is based on HTML5, which enables the visualization to be displayed on our Android panel and any modern Internet browser.



SOX BACnet IP Modbus TCP/IP AAC20-LCD ISMA-D-PA15 Web Server Modbus RTU / BACnet MS/TP AAC20-LCD-D AAC20-M Serial Bus NGITAL OUTPUTS ANALOG OUTPUTS A0/1-WIRE POWER 24/4 C/DC 02 C1 03 04 C2 A1 A2 G0 A3 A4 G0 🞊 👯 G0 G G0 6666 666666 666 66 Digital Signal DALI M-Bus MVR24C2 + VLX2P Up to 64 DALI Ballasts Up to 20 M-Bus Meters







North West Office: Via G. Matteotti 193-203, 21044 Cavaria con Premezzo (VA), Italy North East Office: Via F. Petrarca, 34, 35020 Albignasego (PD), Italy



